

Mode/Channel			Value	Function	Type of control
Mod1	Mod1	8bit			
11	11	9	224-231 232-239 240-247 248-255	Macro 28 Macro 29 Macro 30 Macro 31	step step step step
12	12	10	0-31 32-63 64-95 96-127 128-143 144-159 160-191 192-223 224-255	Shutter,Strobe Shutter closed Shutter open Strobe-effect from slow to fast Shutter open Closing pulses from slow to fast Opening pulses from fast to slow No function Random strobe -effect from slow to fast Shutter open	step step proportional step proportional proportional step proportional step
13	13	11	0-255	Dimmer intensity Dimmer from closed to 100% light output	proportional