D2
power amplifier

The AUDAC D2 delivers an output power of 2 x 200 Watt @ 8 Ohm and 2 x 300 Watt @ 4 Ohm. In bridge mode it can deliver a power of 600 Watt @8 Ohm.



The AUDAC D2 front

On the front of the D series, for each channel, you can find a Volume control to set the individual volume per channel, a Sig led to check if there is a signal present on the appropriate channel, a Clip led to indicate when the signal is too strong and should be reduced, and a Prot led to warn when the protection circuit kicks in, to avoid damage to the amplifier per channel. Of course, the power button with a blue power indicator can be found here too.



The AUDAC D2 rear

Each channel has its own, separate signal input on balanced XLR connector and an output on speaker connector. The D series can be set in stereo or bridge mode for channel 1 + 2, using the appropriate switch. A ground-lift switch is also provided to avoid humming sound produced by ground loops. And of course the power connection can be found here too.

Technical specifications :					
	D2	D3	D4	D5	
RMS Power @ 8 Ohm	2 x 200 W	2 x 300 W	2 x 400 W	2 x 500 W	
RMS Power @ 4 Ohm	2 x 300 W	2 x 450 W	2 x 600 W	2 x 750 W	
RMS Power @ 2 Ohm	n/a	2 x 600 W	2 x 800 W	2 x 1000W	
RMS Power @ 8 Ohm bridged	600 W	900 W	1200 W	1500 W	
RMS Power @ 4 Ohm bridged	n/a	1200 W	1600 W	2000 W	
THD+N		<0,05% @ 8 Ohm 1 Khz			
Signal to noise ratio		> 93 dB			
Slew rate		40 V / µsec			
Frequency response		20 Hz - 20 kHz			
Input Impedance	20	20 kOhm balanced , 10 kOhm unbalanced			
Crosstalk		> 70 dB @ 8 Ohm 1 kHz			
Input sense		0,775 V			
Damping factor	> 200	> 200	> 400	> 400	
Power supply		240 V AC / 50 Hz - 60 Hz			
Protection	DC ; Short	DC; Short circuit; Overheating; Overload; Signal limiting			
Construction		Steel			
Dimensions (WxHxD)		483 x 90 x 385 mm			
Unit height	2 HE	2HE	2HE	2HE	
Weight	21,3 Kg	22,7 Kg	24,0 Kg	26,0 Kg	
Colour		Black			

About Audac :

AUDAC provides a complete range of audio equipment such as amplifiers, loudspeakers, microphones, conference microphones and much more.

