



Mode 1 Channel	Mode 2 Channel	Value	Function	Type of control
7	7	176-183 184-191 192-199 200-207 208-215 216-223 224-231 232-239 240-247 248-255	<b>Colour macros (continue)</b> Macro 22 Macro 23 Macro 24 Macro 25 Macro 26 Macro 27 Macro 28 Macro 29 Macro 30 Macro 31	step step step step step step step step step step
8	8	0-70 71-180 181-255	<b>Effect wheel</b> Full beam Beam shaper Frost filter	step step step
9			<b>No function</b>	
10	9	0-31 32-95 96-127 128-159 160-175 176-191 192-223 224-255	<b>Shutter,stroke,reset</b> Shutter closed Shutter open Strobe-effect from slow to fast (max.10 flashes/s) Shutter closed Pulse-effect in sequences with increasing speed Pulse-effect in sequences with decreasing speed Random strobe-effect with increasing speed Shutter open	step step proportional step proportional proportional proportional step
11	10	0-255	<b>Dimmer intensity</b> Intensity from 0 to 100%	proportional