

The APart CMR5 is a neutral rectangular 100 volt built-in speaker, provided with a 5.25" dual cone woofer. Due to its clear sound reproduction, the CMR5 is very suitable for the distribution of backgroundmusic and microphone calls. This loudspeaker has a 100 Volt 6 watt transformer with several power tappings.

The loudspeaker is easy to install, due to its simple, quick mounting system (4 screws which are hidden behind the loudspeaker grill).

The standard colour is white RAL 9010. As an option the CMR5 can be painted in any RAL colour (Ref; PAINT-CM). Please note that the minimum order quantity for PAINT-CM is 12 pieces.

Also available: In-wall back box for CMR5 (Ref; CMRBBi) On-wall back box for CMR5 (Ref; CMRBB)

TECHNICAL SPECIFICATIONS

APart CMR5

Type Woofer Impedance Transfo Power Tappings **RMS** Power AES Rated Music SPL 1 watt/1 m Frequency Range Dispersion @ 1 kHz @ 4 kHz @ 8 kHz Dimensions Outside (H x W) Cutout (H x W) Depth Weight

Dual cone 5.25" paper cone 8 Ohm / 100V 1,5 - 3 - 6 watt (6.66k - 3.33k - 1.66k) 6 watt 10 watt 90 dB 70 Hz - 18 kHz 180° 120° 45° 237 x 170 mm 210 x 143 mm 65 mm 1.1 Kg