## 5

## APart E-VOL20-BL





The APart E-VOL20-BL is a 100Volt volume control. It is available in black and white color, and can handle up to 20 Watt of power.

It is very durable thanks to the step-by-step attenuation in 11 steps  $+ \; {\sf zero} \;$  position.

The E-VOL 20-BL is designed to handle 24V priority signals. This means that you can always get an announcement out, even to zones where the local volume control is in the 'OFF' position!

If your amplifier has a 24 V priority output, it will send a 24 V signal when you push the talk button on the microphone. The 24 V signal will close a relay on the E-VOL20-BL volume control, and the signal will pass, even when the volume control is in the 'OFF' position. This can be very useful for emergency or evacuation messages.

The E-VOL20-BL is built on a universal chassis that easily can be integrated with Gira, Jung and Euro. Different cover plates are available for the UK market.

## TECHNICAL SPECIFICATIONS

Type Handling Power Voltage 24 V priority Attenuation steps Build-in box Build-on box Dimensions (HxWxD) Weight color also available as Euro 20 Watt 100 Volt Yes 11 + "0" E-MODIN E-MODON 80 x 80 x 45 mm 104 grams E-VOL20-BL : black E-VOL20 : white