



## APart PA4060 AMPLIFIER





This 19" 4 channel power amplifier is very compact and supplies you with 4 x 60 watt in 4 ohm use.

The PA4060 has convectional cooling (no fan) what makes it very quiet and maintenance-free.

The input signals can be linked via the routing switches or via RCA CINCH cables. The amplifier is equiped with build-in limiters and the following controls and indications are available on the front pannel:

- \* Volume left right
- \* Signal protect & limit led per channel
- \* Power on/of

It is advised to order the PA19 mounting bracket in case of 19" rackmount use.



## TECHNICAL SPECIFICATIONS

Input RCA Cinch unbalanced 1V / 10 kOhm
Link: RCA Cinch unbalanced 1V / 10 kOhm

Output 8 Ohm: 4 x 50 watt / 70 watt Max (RMS Program) 4 Ohm: 4 x 60 watt / 90 watt Max

Frequency Response 15 Hz - 30 kHz
Distortion < 0.03%

Dimensions (H x W x D) 44 x 483 x 325 mm

Weight 6.9 Kg

WWW.APART-AUDIO.COM INFO@APART-AUDIO.COM