



APart

APart PXQ2215  
EQUALIZER



The APart PXQ2215 looks like a standard 2 x 15 band EQ, but in real it is much more than that. The PXQ2215 combines the EQ section with a 2 way adjustable X-over at the back. Turning the frequency pot-meter completely to the left, results in a Full range output.

Via this adjustable frequency potentiometer, a perfect balance for your low and mid-high frequencies can be obtained, no matter what acoustic environment you are in. This will result in a cristal clear and above all dynamic sound!

Besides the perfect sound quality, the PXQ2215 saves you rack space as it is only 1 rack unit high.

TECHNICAL SPECIFICATIONS

Type	2 x 15, 2/3 octave, 6 freq. Below 300 Hz, ISO Spacing above 300 Hz
X-over	20-300 Hz adjustable, 24 dB/oct. Linkwitz-Riley
Control Range EQ	+/- 6 dB or 12 dB selectable
Inputs	Balanced XLR 20 kOhm, RCA Cinch 15 kOhm
Outputs	Sub Out / High Fullrange out: XLR balanced + RCA Cinch
Distortion	0.02% (at 1 kHz, all slider at center)
Frequency Response	20 Hz to 50 kHz, -3dB (all slider at center)
Signal to Noise Ratio	> 93 dB
Dimensions (H x W x D)	44 x 483 x 280 mm
Weight	3.5 Kg