HD Digital Signage Player



- High Performance & Stability(40Mps)
- Supports Multiple Display Zones Supports Schedule Function HDMI 1.3 Compliant

- Full HD WMV9 Digital Signage Player
- Supports FTP Auto Download Function



Introduction

Eyezone B1080PX-3 is a full HD digital signage that plays media files from CF memory card without a computer. The media files can be automatically updated at the specific time from an FTP server. What's more, Eyezone B1080PX-3 supports multiple display zones, you can play movie, picture and scrolling text on the screen simultaneously, and the text color can be changed (white/ yellow/ green)

By connecting to S-Video, VGA (1360 \times 768), HDMI (1920 \times 1080P) and Audio, you can play the media contents on any display device for advertising, presentations, training and other media applications.

■ Features































< Optional >







- High-performance and high stability: The resolution and bit rate of video like a blu-ray quality. The source of HD WMV9 MP@HL (Main Profile / High Level) supports resolution up to 1920x1080 (1080P)
- and the maximum bit rate is 40Mbps.
- Supports Multiple Display Zones: Displays the movie, picture (supports png format/ size:150x400/ 96DPI) and scrolling text on the screen simultaneously.
- The display speed of scrolling text can be adjusted, and scrolling text supports multi languages
- (Latin1/ Latin2/ Japanese/ Greek).
- The text color can be changed (white/yellow/green)

 Schedule Function: The B1080PX-3 will auto play the specific file at the specific date.
- Supports multiple file formats: WMV9 and WMA.
- Supports S-Video, HDMI, VGA and Audio output.
- HDMI Output: 480P/ 720P/ 1080i/ 1080P
- HDMI 1.1, 1.2 and 1.3 compliant.
- VGA output supports resolution: 640x480/ 800x600/ 1024x768/ 1280x1024/ 1360x768.
- Supports RS-232 port for computer control with ASCII command (play, stop, pause...etc). Supports CF memory cards. (Suggest using the high speed (150X) CF card)
- Exports the Configuration Value: You can export the configuration value to the CF card.
- The configuration value can be modified on your PC, and can be applied to the B1080PX-3 or others.
- Supports Auto Key Lock Function
- Connect using an Ethernet network cable at up to 100Mbps.
- Supports HTTP Control Function
- Compatible with Windows Media Player 11: Play media files stored in a network computer.
- Supports FTP Auto Download Function: Connect to Remote FTP server and download data to the CF card automatically.
- Supports Download Pause / Resume Function: Continue unfinished downloads upon next session.
- Embedded FTP Server.
- Supports NTP Network (G.M.T) Timer
- Supports Universal Plug and Play (UPnP) and DHCP.
 Supports SLIDE SHOW Function (interval time with 10/ 15/ 30/ 60 seconds).