

LED MICRO SCAN



:: Product Description

- * Ultra compact DMX scanner for mobile DJs and small clubs
- * Based on 10WATT WHITE LED technology:
 - * - Very low power consumption (money saving!)
 - * - Extremely brilliant colors compared to units with halogen lamps
 - * - No lamp replacements!
 - * - Virtually no heat production: no noisy fans
 - * - Lightweight (no lamp transformers needed)
- * Big light output and sharp gobos, thanks to excellent optics
- * 0-100% dimming and ultra fast strobe function
- * Excellent built-in programs for wonderful, ever changing, light shows:
 - * - DMX-control: 5 channels (pan, tilt, color/gobo, strobe, dimmer)
 - * - Standalone: sound activated with internal mic
 - * - Master/slave: wonderful synchronized shows
- * 8 gobos + open, equipped with gobo shaking feature
- * 2 optional remote controllers available:
 - * - CA-8: wired remote for improved master/slave control
 - * - RF-8 Set: wireless RF-remote for improved master/slave control (RF-8SET = RF-8T "transmitter" + RF-8R "receiver")

:: Technical Information

- * Mains Input: AC 100 ~ 240V, 50/60Hz
- * Fuse: 250V 2A fast blow (20mm glass)
- * Sound Control: Internal microphone
- * DMX connections: 3pin XLR male / female
- * DMX channels: 5
- * Lamp: CREE 10W White LED
- * Size: 333 x 156 x 177mm
- * Weight: 3,0kg

:: Extra information and order codes
